

ONKYO TX-5000



Specifications

Tuning range: FM, MW

Power output: 65 watts per channel into 8 Ω (stereo)

Frequency response: 15Hz to 30kHz

Total harmonic distortion: 0.03%

Damping factor: 50

Input sensitivity: 2.5mV (MM), 150mV (line)

Signal to noise ratio: 86dB (MM), 95dB (line)

Output: 150mV (line)

Semiconductors: 2 x FET, 51 x transistors, 16 x IC, 50 x diodes

Dimensions: 540 x 146 x 400mm

Weight: 15kg